

## HYBRID-HIGH RELIABILITY RADIATION HARDENED DC-DC CONVERTER

## 28V Input, Single/Dual Output

### Description


The LS-Series of DC-DC converters are, high reliability devices designed for hostile radiation hardened environments. The LS-Series provide up to 30 watts output power, small size, low weight, integrated EMI filtering and a high tolerance to environmental stresses such as radiation, temperature extremes, mechanical shock, and vibration. Extensive documentation including, thermal analysis, stress analysis and reliability predictions are available.

The LS-Series of converters incorporate a fixed frequency single forward topology with magnetic feedback and an internal EMI filter. These converters are capable of meeting the conducted emissions requirements of MIL-STD-461C without any additional components. All models include an external inhibit port and have an adjustable output voltage. They are enclosed in a hermetic 1.5" x 2.3" x 0.425" steel package and weigh less than 80 grams. The package utilizes rugged ceramic feed-through copper core pins and is sealed using parallel seam welding.

The LS-Series of DC-DC converters provide same mechanical outline, power ratings, for backward pin compatibility, to their lower radiation tolerant counterpart M3L and Military series ATS DC-DC converters. The common platform design allows for similarity between military and space system architectures. For higher output power applications the HM, M3H and M3G-Series of DC-DC converters are recommended.

Manufactured in a facility fully qualified to MIL-PRF-38534, these converters are fabricated utilizing DLA Land and Maritime qualified processes. For available screening options, refer to device screening table in the data sheet.

Variations in electrical specifications and screening to meet custom requirements can be accommodated.



### Features

- 18 to 40V DC Input Range
- Total Ionization Dose > 100 kRad(Si)
- SEE Hardened to LET (Heavy Ions) up to 82 MeV•cm<sup>2</sup>/mg (SEU, SEL, SEGB, SEGR)
- Internal EMI filter; Converter Capable of meeting MIL-STD-461C CE03
- Low Weight, < 80 grams
- Magnetically Coupled Feedback
- Up to 30W Output Power
- Single and Dual Output Models Include 1.5, 2.5, 3.3, 5, 12, 15, ±5, ±12 and ±15V
- High Efficiency - to 83%
- 100MΩ @ 500V<sub>DC</sub> Isolation
- Under Voltage Protection
- Short Circuit and Overload Protection
- Adjustable Output Voltage
- External Inhibit
- > 4,000,000 Hour MTBF (SF)
- Standard Microcircuit Drawings Available

### Applications

- Geo Synchronous Satellite
- Low Earth Orbit
- Deep Space Probe
- Communication and Display Systems
- Payload and Experiment LVPS

## Circuit Description

The LS-Series converters utilize a single-ended forward topology with resonant reset. The nominal switching frequency is 500 kHz. Electrical isolation and tight output regulation are achieved through the use of a magnetically coupled feedback. Voltage feed-forward with duty factor limiting provides high line rejection and protection against output over voltage in the event of an internal control loop failure.

An internal EMI filter allows the converter to meet the conducted emissions requirements of MIL-STD-461C on the input power leads.

Output current is limited under any load fault condition to approximately 125% of rated. An overload condition causes the converter output voltage to drop below nominal. The converter will resume normal operation when the load current is reduced below the current limit point. This protects the converter from both overload and short circuit conditions. The current limit point exhibits a slightly negative temperature coefficient to reduce the possibility of thermal runaway.

An external inhibit port is provided to control converter operation. The converter's operation is inhibited when this pin is pulled low. It is intended to be driven by an open collector logic device. The pin may be left open for normal operation and has a nominal open circuit voltage of 11V with respect to the input return (pin 2).

The output voltage of all models can be adjusted using a single external resistor.

## Design Methodology

The LS-Series was developed using a proven conservative design methodology derived from other space level designs that includes selection of established reliability components and fully de-rating to the requirements of MIL-STD-975 except for the CDR type of capacitors, a capacitor with 50V rating is used for in-circuit voltage stress of less than 10V. A magnetic feedback circuit is utilized instead of opto -couplers to minimize temperature, aging and radiation sensitivity. PSpice was used extensively to predict and optimize circuit performance for both beginning and end-of-life. Thorough design analyses include stress, thermal, and reliability (MTBF).

## Specifications

Absolute Maximum Ratings		Recommended Operating Conditions	
Input Voltage range	-0.5V <sub>DC</sub> to +60V <sub>DC</sub>	Input Voltage range <sup>1</sup>	+18V <sub>DC</sub> to +40V <sub>DC</sub>
Output power	Internally limited	Output power	0 to Max. Rated
Lead Temperature	+300°C for 10 seconds	Operating case temperature	-55°C to +85°C
Operating Case temperature	-55°C to +125°C (Note 13)	Operating case temperature <sup>2</sup>	-55°C to +70°C
Storage temperature	-55°C to +135°C		

1. Meets MIL-STD-1547, MIL-STD-975 and NASA EEE-INST-002 up to the input voltage at 38.6V.

2. Meets de-rating per MIL-STD-975

## Electrical Performance Characteristics

Parameter	Group A Subgroup	Conditions -55°C ≤ T <sub>C</sub> ≤ +85°C V <sub>IN</sub> = 28V DC ± 5%, C <sub>L</sub> = 0 unless otherwise specified	Limits			Unit
			Min	Nom	Max	
Input Voltage			18	28	40	V
Output Voltage (V <sub>OUT</sub> )						
LS2801R5S	1	I <sub>OUT</sub> = 100% rated load Note 4	1.47	1.50	1.53	V
LS2802R5S	1		2.47	2.50	2.53	
LS2803R3S	1		3.27	3.30	3.33	
LS2805S	1		4.95	5.00	5.05	
LS2812S	1		11.88	12.00	12.12	
LS2815S	1		14.85	15.00	15.15	
LS2805D	1		±4.95	±5.00	±5.05	
LS2812D	1		±11.88	±12.00	±12.12	
LS2815D	1		±14.85	±15.00	±15.15	
LS2801R5S	2,3	I <sub>OUT</sub> = 100% rated load Note 4, 14	1.43		1.57	
LS2802R5S	2,3		2.43		2.57	
LS2803R3S	2,3		3.23		3.37	
LS2805S	2,3		4.90		5.10	
LS2812S	2,3		11.76		12.24	
LS2815S	2,3		14.70		15.30	
LS2805D	2,3		±4.90		±5.10	
LS2812D	2,3		±11.76		±12.24	
LS2815D	2,3		±14.70		±15.30	
Output power (P <sub>OUT</sub> )						
LS2801R5S	1,2,3	V <sub>IN</sub> = 18, 28, 40 Volts, Note 2	0		12	W
LS2802R5S			0		20	
LS2803R3S			0		25	
All Others			0		30	
Output current (I <sub>OUT</sub> )						
LS2801R5S	1,2,3	V <sub>IN</sub> = 18, 28, 40 Volts, Note 2	0		8.0	A
LS2802R5S			0		8.0	
LS2803R3S			0		7.57	
LS2805S			0		6.0	
LS2812S			0		2.5	
LS2815S			0		2.0	
LS2805D			0		4.8	
LS2812D			0		2.3	
LS2815D			0		1.6	
		Either Output, Note 3				
		Either Output, Note 3				
		Either Output, Note 3				

For Notes to Electrical Performance Characteristics, refer to page 6.

**Electrical Performance Characteristics (continued)**

Parameter	Group A Subgroup	Conditions -55°C ≤ T <sub>C</sub> ≤ +85°C V <sub>IN</sub> = 28V DC ± 5%, C <sub>L</sub> = 0 unless otherwise specified	Limits			Unit
			Min	Nom	Max	
Line regulation (VR <sub>LINE</sub> )	1,2,3	V <sub>IN</sub> = 18, 28, 40 Volts I <sub>OUT</sub> = 0, 50%, 100% rated, Note 4	-0.5		0.5	%
Load regulation (VR <sub>LOAD</sub> ) LS2801R5S LS2802R5S All others	1,2,3	V <sub>IN</sub> = 18, 28, 40 Volts I <sub>OUT</sub> = 0, 50%, 100% rated, Note 4	-2.0 -1.2 -1.0		2.0 1.2 1.0	%
Cross regulation (VR <sub>CROSS</sub> ) LS2805D LS2812D LS2815D	1,2,3	V <sub>IN</sub> = 18, 28, 40 Volts Duals only, Note 5	-5.0 -3.0 -3.0		5.0 3.0 3.0	%
Input Current, no load (I <sub>IN</sub> ) LS2801R5S LS2802R5S LS2803R3S LS2805S LS2812S LS2815S LS2805D LS2812D LS2815D	1,2,3	I <sub>OUT</sub> = 0, Pin 4 open			60 60 60 70 70 70 70 100 100	mA
Input current inhibited	1,2,3	Pin 4 shorted to pin 2			8.0	mA
Output Ripple, (V <sub>RIP</sub> ) LS2801R5S LS2802R5S LS2803R3S LS2805S LS2812S LS2815S LS2805D LS2812D LS2815D	1,2,3	V <sub>IN</sub> = 18, 28, 40 Volts I <sub>OUT</sub> = 100% rated load Notes 4, 6			35 35 35 50 70 80 80 80 80	mVp-p
Switching frequency (F <sub>S</sub> )	1,2,3		425	500	575	kHz
Efficiency (E <sub>FF</sub> ) LS2801R5S LS2802R5S LS2803R3S LS2805S LS2812S LS2815S LS2805D LS2812D LS2815D	1,2,3	I <sub>OUT</sub> = 100% rated load Note 4	61 68 72 78 78 78 79 79 79	64 71 76 82 82 82 83 83 83		%

For Notes to Electrical Performance Characteristics, refer to page 6.

**Electrical Performance Characteristics (continued)**

Parameter	Group A Subgroup	Conditions -55°C ≤ T <sub>C</sub> ≤ +85°C V <sub>IN</sub> = 28V DC ± 5%, C <sub>L</sub> = 0 unless otherwise specified	Limits			Unit
			Min	Nom	Max	
Enable Input (Inhibit Function) open circuit voltage drive current (sink) voltage range		Note 1	9.5 -0.5		12 5.0 50	V mA V
Current Limit Point Expressed as a percentage of full rated load current	1,2,3	V <sub>OUT</sub> = 90% of Nominal, Note 4	105		145	%
Power dissipation, load fault (P <sub>D</sub> )	1,2,3	Short Circuit, Overload, Note 8			14	W
Output response to step load changes (V <sub>TLD</sub> )	4,5,6	Half Load to/from Full Load, Notes 4,9	-300		300	mVpk
Recovery time, step load changes (T <sub>TLD</sub> )	4,5,6	Half Load to/from Full Load, Note 4,9,10			200	μs
Output response to step line changes (V <sub>TLN</sub> )		18V to/from 40V I <sub>OUT</sub> = 100% rated load, Notes 1,4,11	-300		300	mVpk
Recovery Time, step line changes (T <sub>TLN</sub> )		18V to/from 40V I <sub>OUT</sub> = 100% rated load, Notes 1,4,10,11			200	μs
Turn-on Overshoot (V <sub>OS</sub> ) LS2801R5S LS2802R5S LS2803R3S LS2805S LS2812S LS2815S LS2805D LS2812D LS2815D Turn-on Delay (T <sub>DLY</sub> )	4,5,6	10% Load, Full Load Notes 4,12			150 250 330 500 1000 1000 500 1000 1000 10	mV          ms
Capacitive Load (C <sub>L</sub> ) LS2801R5S LS2802R5S LS2803R3S LS2805S LS2812S LS2815S LS2805D LS2812D LS2815D		I <sub>OUT</sub> = 100% rated load No effect on DC performance Notes 1, 4, 7  Each output on duals			2500 2500 2200 1000 180 120 500 90 60	μF

For Notes to Electrical Performance Characteristics, refer to page 6


## Electrical Performance Characteristics (continued)

Parameter	Group A Subgroup	Conditions -55°C ≤ T <sub>C</sub> ≤ +85°C V <sub>IN</sub> = 28V DC ± 5%, C <sub>L</sub> = 0 unless otherwise specified	Limits			Unit
			Min	Nom	Max	
Line Rejection	1	I <sub>OUT</sub> = 100% rated load DC to 50 kHz, Notes 1, 4	35	50		dB
Isolation	1	Input to Output or Any Pin to Case except Pin 3, test @ 500V <sub>DC</sub>	100			MΩ
Device Weight					80	g
MTBF		MIL-HDBK-217F2, SF, 35°C	4.0 x 10 <sup>6</sup>			Hr

### Notes for Electrical Performance Characteristics Table

- Parameter is tested as part of design characterization or after design changes. Thereafter, parameter shall be guaranteed to the limits specified.
- Parameter verified during line and load regulation tests.
- Output load current must be distributed such that at least 20% of the total load current is being provided by one of the outputs.
- Load current split equally between outputs on dual output models.
- Cross regulation is measured with 20% rated load on output under test while changing the load on the other output from 20% to 80% of rated.
- Guaranteed for a D.C. to 20MHz bandwidth. Tested using a 20kHz to 10MHz bandwidth using the circuit on page 6.
- Capacitive load may be any value from 0 to the maximum limit without compromising dc performance. For a capacitive load in excess of the maximum limit, consult the factory.
- Overload power dissipation is defined as the device power dissipation with the load set such that V<sub>OUT</sub> = 90% of nominal.
- Load step transition time ≤ 10μs.
- Recovery time is measured from the initiation of the transient to where V<sub>OUT</sub> has returned to within ±1% of its steady state value.
- Line step transition time ≤ 100μs.
- Turn-on delay time from either a step application of input power or a logic low to a logic high transition on the inhibit pin (pin 4) to the point where V<sub>OUT</sub> = 90% of nominal.
- For operation at temperatures between +85°C and 125°C, de-rate the maximum output power linearly from 100% to 75%.
- End of Life (EOL) is ±3%

**Fig. 1 - Circuit for measuring Output Ripple Voltage**



## Radiation Performance Characteristics

Test Inspection	Method	Min	Typ	Unit
Total Ionizing Dose (Gamma)	MIL-PRF-883, Method 1019.5 Operating bias applied during exposure, Full Rated Load, $V_{IN} = 28V$	100		kRads(Si)
Single Event Effects SEU, SEL, SEGR, SEB	Heavy Ions (LET) Operating bias applied during exposure, Full Rated Load, $V_{IN} = 28V$ <b>Test lab: Cyclotron Institute</b> <b>Texas A &amp; M University</b>	82		MeV•cm <sup>2</sup> /mg

IR HiRel currently does not have a DLA Land and Maritime certified Radiation Hardness Assurance Program.

## LS Series Output Voltage Adjustment

Output of LS series can be adjusted to be greater or less than the nominal output voltage with an external resistor. However, the ranges of the output voltages are limited depending on the model as specified in Table 1 and 2. An approximate value of the resistor can be determined using the following formula.

**For Single Output Model:**

$$R_{adj} = \frac{A - (B * V_{out})}{(C * V_{out}) - D}$$

**For Dual Output Model:**

$$R_{adj} = \frac{A - (B * 2 * V_{out})}{(C * 2 * V_{out}) - D}$$

**Where:**

**R<sub>adj</sub>** is the value of the external resistor in kilo-Ohms, R<sub>down</sub> or R<sub>up</sub> in Figure 1 or 2. Power rating of the resistor shall be ≥ 0.125W. Metal film resistor with temperature coefficient of ≤ ±50 ppm and tolerance of ≤ 1% is recommended. However, the final selection is dependent on specific design requirements.

**V<sub>ovp</sub>** is the output voltage in volts.

**A, B, C and D** are unique constants depending on every model as shown in Table 1 for single output models and Table 2 for dual output models.

**Table 1: Single Output Voltage Ranges and Constants**

Model	Output Voltage Range (V) (1)	A	B	C	D
LS2801R5S	1.500 to 1.600	69.65	32.39	8.75	13.13
	1.400 to 1.500	56.85	40.47	7.14	10.72
LS2802R5S	2.500 to 2.750	48.42	13.04	3.52	8.81
	2.250 to 2.500	39.52	21.19	2.88	7.19
LS2803R3S	3.300 to 3.630	43.48	9.25	2.50	8.25
	2.970 to 3.300	35.48	16.18	2.04	6.73
LS2805S	5.000 to 5.500	119.48	20.00	2.27	11.36
	4.500 to 5.000	97.52	29.31	1.85	9.27
LS2812S	12.000 to 13.200	295.22	19.98	2.27	27.24
	10.800 to 12.000	241.01	53.31	1.85	22.24
LS2815S	15.000 to 16.500	370.61	19.98	2.27	34.05
	13.500 to 15.000	302.55	63.61	1.85	27.80



**Table 2: Dual Output Voltage Ranges and Constants**

Model	Voltage Range of Each Output ( $\pm V_{out}$ ) (1)	A	B	C	D
LS2805D	$\pm 5.000$ to $\pm 5.500$	196.91	17.12	1.71	17.12
	$\pm 4.500$ to $\pm 5.000$	160.74	31.11	1.40	13.97
LS2812D	$\pm 12.000$ to $\pm 13.200$	475.43	17.05	1.71	40.92
	$\pm 10.800$ to $\pm 12.000$	388.10	58.04	1.39	33.41
LS2815D	$\pm 15.000$ to $\pm 16.500$	594.31	17.03	1.70	51.09
	$\pm 13.500$ to $\pm 15.000$	485.10	69.47	1.39	41.70


Note:

(1). Also the minimum and maximum adjustment limits of the output voltage.


### Placement of R<sub>adj</sub>



An external resistor must be added in order to trim the output voltage of an LS converter. The placement of an R<sub>adj</sub> resistor (R<sub>down</sub> or R<sub>up</sub>) must be as shown in Figure 1 for single output models and as per Figure 2 for dual output models. Please note that the connections are made to the specific pins. R<sub>up</sub> is placed across Out Return and Out Adj pins for output voltage greater than nominal output. Similar connections apply for the dual output models.



**Figure 1: Radj Placement for Single Output Model**





**Figure 2: Radj Placement for Dual Output Model**









The block diagram illustrates the internal components and signal flow of a Class D audio amplifier. Key blocks include:


- EMI Filter:** Processes the +V input (1) and Input Return (2).
- Bias Supply:** Provides a +5V supply to the Level Translator & FET Driver.
- Level Translator & FET Driver:** Receives the +10.5V supply and the Inhibit signal (4). It drives the FETs of the push-pull output stage.
- Short Ckt & Overload Protection:** Monitors the output stage for faults.
- Oscillator:** Generates the switching signal for the PWM block.
- Logic:** Includes a comparator (>=1) and a Ramp Generator that work with the PWM block to generate the pulse-width modulated signal.
- Sample and Hold:** Samples the input signal and holds it for the PWM generation.
- Feedback Trigger:** Provides feedback from the output to the input stage.
- EA (Error Amplifier):** Amplifies the error signal from the feedback loop.
- Output Stage:** Consists of a push-pull FET pair driving a transformer-coupled load. The output is taken from the secondary of the transformer, passing through a resistor network to the Output Return (5) and an Output Adjust (6) point.

External connections are labeled: +V input (1), Input Return (2), Inhibit (4), Case Ground (3), +V out (7), Output Return (5), and Output Adjust (6).

The diagram illustrates a power supply system with the following components and connections:

- Inputs:** +V input (1), Input Return (2), Inhibit (4), Case Ground (3).
- Power Regulation:**
  - EMI Filter:** Connected to the +V input and Input Return.
  - Bias Supply:** Provides +5V and +10.5V rails.
  - Level Translator & FET Driver:** Receives the +5V rail and controls the FET driver.
  - Short Ckt & Overload Protection:** Receives feedback from the output and provides a signal to the Level Translator & FET Driver.
- Control and Timing:**
  - Oscillator:** Provides a clock signal to the >=1 block and the PWM block.
  - >=1:** A logic block that outputs a signal to the PWM block.
  - PWM:** A pulse-width modulator that outputs a signal to the Ramp Generator.
  - Ramp Generator:** Generates a ramp signal for the feedback loop.
  - Sample and Hold:** Samples the output voltage and provides a signal to the Feedback Trigger.
  - Feedback Trigger:** Provides a signal to the Level Translator & FET Driver.
- Output Stage:**
  - FET Driver:** Controls the power MOSFET.
  - Power MOSFET:** The main switching transistor.
  - Output Filter:** Consists of an inductor and capacitors, connected to the +V out (8) and -V out (6) terminals.
  - Output Adjust:** A potentiometer used to adjust the output voltage, connected to the -V out (6) terminal.

## Mechanical Outline



## Pin Designation (Single/Dual)

Pin #	Single	Dual
1	+ Input	+ Input
2	Input Return	Input Return
3	Case Ground	Case Ground
4	Inhibit	Inhibit
5	Output Adjust	Output Adjust
6	Output Return	-Output
7	+ Output	Output Return
8	NC	+ Output

## Device Screening


Part Number Designator		/EM ①	/CK ②	5962-xxxxxxxKyy ③
Compliance Level	MIL-PRF-38534	—	K level compliant	Class K SMD
Certification Mark		—	CK	QML
Screening Requirement	MIL-STD-883 Method	—	—	—
Temperature Range	—	Room Temperature	-55°C to +85°C	-55°C to +85°C
Element Evaluation	MIL-PRF-38534	N/A	Class K	Class K
Non-Destructive Bond Pull	2023	N/A	Yes	Yes
Internal Visual	2017	IR Defined	Yes	Yes
Temperature Cycle	1010	N/A	Cond C	Cond C
Constant Acceleration	2001, Y1 Axis	N/A	3000 Gs	3000 Gs
PIND	2020	N/A	Cond A	Cond A
Burn-In	1015	N/A	320 hrs @ 125°C (2 x 160 hrs)	320 hrs @ 125°C (2 x 160 hrs)
Final Electrical (Group A)	MIL-PRF-38534 & Specification	Room Temperature	-55°C, +25°C, +85°C	-55°C, +25°C, +85°C
PDA	MIL-PRF-38534	N/A	2%	2%
Seal, Fine and Gross	1014	N/A	Cond CH	Cond CH
Radiographic	2012	N/A	Yes	Yes
External Visual	2009	IR Defined	Yes	Yes

### Notes:

- ① **"EM" grade** parts are strictly intended to permit the customer to determine the electrical functionality of the device in the customer's application in ambient conditions. The use of EM devices in production applications presents an unquantifiable risk of failure and IR HiRel disclaims all responsibility for such failure.
- ② **"CK" grade** is the flight model (FM) compliant to K Level screening as defined in the DLA Land and Maritime MIL-PRF-38534 requirements, but is not necessarily a DLA Land and Maritime qualified SMD per MIL-PRF-38534. The governing document for this part number designator is the IR HiRel datasheet (this document). Radiation rating as stated in the "Radiation Performance Characteristics" section, is verified by analysis and test per IR HiRel internal procedure. The part is marked with the IR base part number and the "CK" certification mark.
- ③ **"Class K SMD" grade** has a DLA qualified SMD per DLA MIL-PRF-38534 Class K which is the governing document for this part. The part is marked with the IR base part number, the SMD part number and the "QML" certification mark.



### Part Numbering



## Orderable Part Numbers and DLA SMD Numbers

If a DLA SMD is available as listed in the table below, such model shall be ordered using the DLA SMD number. Otherwise the model shall be ordered using the part number nomenclature.

Reference IR Base Model	Orderable Part Number	Lead finish
LS2801R5S/CKA	<b>5962-0523801KXA</b>	Solder Dipped
LS2801R5S/CKC	<b>5962-0523801KXC</b>	Gold Plated
LS2803R3S/CKA	<b>5962-0523901KXA</b>	Solder Dipped
LS2803R3S/CKC	<b>5962-0523901KXC</b>	Gold Plated
LS2805S/CKA	<b>5962-0524001KXA</b>	Solder Dipped
LS2805S/CKC	<b>5962-0524001KXC</b>	Gold Plated
LS2812S/CKA	<b>5962-0624101KXA</b>	Solder Dipped
LS2812S/CKC	<b>5962-0624101KXC</b>	Gold Plated
LS2815S/CKA	<b>5962-0624201KXA</b>	Solder Dipped
LS2815S/CKC	<b>5962-0624201KXC</b>	Gold Plated
LS2805D/CKA	<b>5962-1022401KXA</b>	Solder Dipped
LS2805D/CKC	<b>5962-1022401KXC</b>	Gold Plated
LS2812D/CKA	<b>5962-0524101KXA</b>	Solder Dipped
LS2812D/CKC	<b>5962-0524101KXC</b>	Gold Plated
LS2815D/CKA	<b>5962-0524201KXA</b>	Solder Dipped
LS2815D/CKC	<b>5962-0524201KXC</b>	Gold Plated

### **IMPORTANT NOTICE**

The information given in this document shall be in no event regarded as guarantee of conditions or characteristic. The data contained herein is a characterization of the component based on internal standards and is intended to demonstrate and provide guidance for typical part performance. It will require further evaluation, qualification and analysis to determine suitability in the application environment to confirm compliance to your system requirements.

With respect to any example hints or any typical values stated herein and/or any information regarding the application of the product, Infineon Technologies hereby disclaims any and all warranties and liabilities of any kind including without limitation warranties on non-infringement of intellectual property rights and any third party.

In addition, any information given in this document is subject to customer's compliance with its obligations stated in this document and any applicable legal requirements, norms and standards concerning customer's product and any use of the product of Infineon Technologies in customer's applications.

The data contained in this document is exclusively intended for technically trained staff. It is the responsibility of any customer's technical departments to evaluate the suitability of the product for the intended applications and the completeness of the product information given in this document with respect to applications.

For further information on the product, technology, delivery terms and conditions and prices, please contact your local sales representative or go to ([www.infineon.com/irhirel](http://www.infineon.com/irhirel)).

### **WARNING**

Due to technical requirements products may contain dangerous substances. For information on the types in question, please contact your nearest Infineon Technologies office.