

IRHM57Z60 PD-93786D

Radiation Hardened Power MOSFET Thru-Hole (TO-254AA) 30V, 35A, N-channel, R5 Technology

Features

- Single event effect (SEE) hardened
- Repetitive avalanche ratings
- Dynamic dv/dt ratings
- Simple drive requirements
- Hermetically sealed
- Electrically isolated
- Ceramic eyelets
- ESD rating: Class 3B per MIL-STD-750, Method 1020

Potential Applications

- DC-DC converter
- Motor drives

Product Validation

Qualified to according to MIL-PRF-19500 for space applications

Description

IR HiRel R5 technology provides high performance power MOSFETs for space applications. This technology has over a decade of proven performance and reliability in satellite applications. These devices have been characterized for both Total Dose and Single Event Effects (SEE). The combination of low $R_{DS(on)}$ and low gate charge reduces the power losses in switching applications such as DC to DC converters and motor control. These devices retain all of the well-established advantages of MOSFETs such as voltage control, fast switching and temperature stability of electrical parameters.

Ordering Information

Table 1 Ordering options

able 1 Ordering options							
Part number	Package	Screening Level	TID Level				
IRHM57Z60	TO-254AA	сотѕ	100 krad(Si)				
IRHM57Z60SCS	TO-254AA	S-Level	100 krad(Si)				
IRHM53Z60	TO-254AA	сотѕ	300 krad(Si)				
IRHM53Z60SCS	TO-254AA	S-Level	300 krad(Si)				
IRHM54Z60	TO-254AA	COTS	500 krad(Si)				
IRHM54Z60SCS	TO-254AA	S-Level	500 krad(Si)				

Product Summary

BV_{DSS}: 30V

• I_D: 35A

• $R_{DS(on),max}$: 9.5m Ω

Q_{G,max}: 200nC



IRHM57Z60

Radiation Hardened Power MOSFET Thru-Hole (TO-254AA)



Table of contents

Table of contents

Featı	tures	1
Pote	ential Applications	1
	duct Validation	
	cription	
	ering Information	
	le of contents	
1	Absolute Maximum Ratings	
2	Device Characteristics	
2.1	Electrical Characteristics (Pre-Irradiation)	
2.2	Source-Drain Diode Ratings and Characteristics (Pre-Irradiation)	5
2.3	Thermal Characteristics	5
2.4	Radiation Characteristics	
2.4.1	Electrical Characteristics — Post Total Dose Irradiation	5
2.4.2	Single Event Effects — Safe Operating Area	6
3	Electrical Characteristics Curves (Pre-irradiation)	7
4	Test Circuits (Pre-irradiation)	10
5	Package Outline	11
Revis	ision history	12



Absolute Maximum Ratings

1 Absolute Maximum Ratings

 Table 2
 Absolute Maximum Ratings (Pre-Irradiation)

Symbol Parameter		Value	Unit
I_{D1} @ V_{GS} = 12V, T_{C} = 25°C	Continuous Drain Current	35*	Α
I_{D2} @ V_{GS} = 12V, T_{C} = 100°C	Continuous Drain Current	35*	Α
I_{DM} @ $T_C = 25^{\circ}C$	Pulsed Drain Current ¹	140	Α
$P_D @ T_C = 25^{\circ}C$	Maximum Power Dissipation	250	W
	Linear Derating Factor	2.0	W/°C
V_{GS}	Gate-to-Source Voltage	± 20	V
E _{AS}	Single Pulse Avalanche Energy ²	500	mJ
I_{AR}	Avalanche Current ¹	35	Α
E _{AR}	Repetitive Avalanche Energy ¹	25	mJ
dv/dt	Peak Diode Reverse Recovery ³	1.1	V/ns
T _J Operating Junction and Storage Temperature Range		-55 to +150	°C
Lead Temperature		300 (0.063 in. /1.6 mm from case for 10s)	
	Weight	9.3 (Typical)	g

^{*} Current is limited by package

 $^{^{\}rm 1}$ Repetitive Rating; Pulse width limited by maximum junction temperature.

 $^{^2}$ V_{DD} = 25V, starting T_J = 25°C, L = 0.8mH, Peak I_L = 35A, V_{GS} = 12V

 $^{^3}$ $I_{SD} \leq 35 A,\, di/dt \leq 132 A/\mu s,\, V_{DD} \leq 30 V,\, T_J \leq 150 ^{\circ} C$



Device Characteristics

2 Device Characteristics

2.1 Electrical Characteristics (Pre-Irradiation)

Table 3 Static and Dynamic Electrical Characteristics @ T_j = 25°C (Unless Otherwise Specified)

Symbol	Parameter	Min.	Тур.	Max.	Unit	Test Conditions	
BV _{DSS}	Drain-to-Source Breakdown Voltage	30	_	_	V	$V_{GS} = 0V, I_D = 1.0 mA$	
$\Delta BV_{DSS}/\Delta T_{J}$	Breakdown Voltage Temp. Coefficient	_	0.028	_	V/°C	Reference to 25°C, I _D = 1.0mA	
R _{DS(on)}	Static Drain-to-Source On-State Resistance	_	_	9.5	mΩ	$V_{GS} = 12V$, $I_{D2} = 35A^{1}$	
$V_{GS(th)}$	Gate Threshold Voltage	2.0	_	4.0	V	$V_{DS} = V_{GS}$, $I_D = 1mA$	
Gfs	Forward Transconductance	45	_	_	S	$V_{DS} = 15V$, $I_{D2} = 35A^{1}$	
	Zama Cata Valta da Busin Comunat	_	_	10		$V_{DS} = 24V, V_{GS} = 0V$	
I_{DSS}	Zero Gate Voltage Drain Current	_	_	25	μΑ	$V_{DS} = 24V, V_{GS} = 0V, T_{J} = 125^{\circ}C$	
	Gate-to-Source Leakage Forward		_	100	^	V _{GS} = 20V	
I_{GSS}	Gate-to-Source Leakage Reverse	_	_	-100	nA	V _{GS} = -20V	
Q _G	Total Gate Charge	_	_	200		I _{D1} = 35A	
Q_{GS}	Gate-to-Source Charge	_	_	55	nC	$V_{DS} = 15V$ $V_{GS} = 12V$	
$Q_{\sf GD}$	Gate-to-Drain ('Miller') Charge	_	_	40			
$t_{d(on)}$	Turn-On Delay Time	_	_	35		I _{D1} = 35A **	
t _r	Rise Time	_	_	125		$V_{DD} = 15V$	
$t_{d(off)}$	Turn-Off Delay Time	_	_	80	ns	$R_G = 2.35\Omega$	
t _f	Fall Time	_	_	50		$V_{GS} = 12V$	
L _s +L _D	Total Inductance	_	6.8	_	nH	Measured from Drain lead (6mm / 0.25 in from package) to Source lead (6mm/ 0.25 in from package) with Source wire internally bonded from Source pin to Drain pad	
C _{iss}	Input Capacitance		9720			$V_{GS} = 0V$	
C _{oss}	Output Capacitance	_	4230	_	pF	$V_{DS} = 25V$	
C _{rss}	Reverse Transfer Capacitance	_	56	_		f = 1.0MHz	

^{**} Switching speed maximum limits are based on manufacturing test equipment and capability.

-

 $^{^{1}}$ Pulse width \leq 300 $\mu s;$ Duty Cycle \leq 2%



Device Characteristics

2.2 Source-Drain Diode Ratings and Characteristics (Pre-Irradiation)

Table 4 Source-Drain Diode Characteristics

Symbol	Parameter	Min.	Тур.	Max.	Unit	Test Conditions	
Is	Continuous Source Current (Body Diode)	_	_	35	Α		
I _{SM}	Pulsed Source Current (Body Diode) ¹	_	_	140	Α		
V_{SD}	Diode Forward Voltage	_	_	1.2	V	$T_J = 25$ °C, $I_S = 35A$, $V_{GS} = 0V^2$	
t _{rr}	Reverse Recovery Time	_	_	153	ns	$T_J = 25$ °C, $I_F = 35A$, $V_{DD} \le 25V$	
Q _{rr}	Reverse Recovery Charge	_	_	324	nC	di/dt = 100A/μs ²	
t _{on}	Forward Turn-On Time	Intrinsic turn-on time is negligible (turn-on is dominated by L _S +L _D)					

2.3 Thermal Characteristics

Table 5 Thermal Resistance

Symbol	Parameter	Min.	Тур.	Max.	Unit
$R_{\theta JC}$	Junction-to-Case	1	_	0.50	
$R_{\theta CS}$	Junction-to-Sink	-	0.21	_	°C/W
$R_{\theta JA}$	Junction-to- Ambient (Typical socket mount)	1	_	48	

2.4 Radiation Characteristics

IR HiRel radiation hardened MOSFETs are tested to verify their radiation hardness capability. The hardness assurance program at IR HiRel is comprised of two radiation environments. Every manufacturing lot is tested for total ionizing dose (per notes 3 and 4) using the TO-3 package. Both pre- and post-irradiation performance are tested and specified using the same drive circuitry and test conditions in order to provide a direct comparison.

2.4.1 Electrical Characteristics — Post Total Dose Irradiation

Table 6 Electrical Characteristics @ T_J = 25°C, Post Total Dose Irradiation ^{3, 4}

Cbl	B	Up to 500	krad (Si)⁵		T 6	
Symbol	Parameter	Min.	Max.	Unit	Test Conditions	
BV _{DSS}	Drain-to-Source Breakdown Voltage	30	_	V	$V_{GS} = 0V, I_D = 1.0 \text{mA}$	
$V_{GS(th)}$	Gate Threshold Voltage	2.0	4.0	V	$V_{DS} = V_{GS}, I_{D} = 1.0 \text{mA}$	
I _{GSS}	Gate-to-Source Leakage Forward	_	100	^	V _{GS} = 20V	
	Gate-to-Source Leakage Reverse	_	-100	nA	V _{GS} = -20V	
I _{DSS}	Zero Gate Voltage Drain Current	_	10	μΑ	$V_{DS} = 24V, V_{GS} = 0V$	
R _{DS(on)}	Static Drain-to-Source On-State Resistance (TO-3) ²	_	4	mΩ	V _{GS} = 12V, I _{D2} = 35A	
R _{DS(on)}	Static Drain-to-Source On-State Resistance (TO-254AA) ²	_	9.5	mΩ	V _{GS} = 12V, I _{D2} = 35A	
$\overline{V_{SD}}$	Diode Forward Voltage	_	1.2	V	$V_{GS} = 0V, I_F = 35A$	

 $^{^{\}rm 1}$ Repetitive Rating; Pulse width limited by maximum junction temperature.

5 of 13

 $^{^2}$ Pulse width \leq 300 $\mu s;$ Duty Cycle \leq 2%

 $^{^3}$ Total Dose Irradiation with V_{GS} Bias. V_{GS} = 12V applied and V_{DS} = 0 during irradiation per MIL-STD-750, Method 1019, condition A.

 $^{^4}$ Total Dose Irradiation with V_{DS} Bias. V_{DS} = 24V applied and V_{GS} = 0 during irradiation per MIL-STD-750, Method 1019, condition A.

⁵ Part numbers IRHM57Z60, IRHM53Z60 and IRHM54Z60



Device Characteristics

2.4.2 Single Event Effects — Safe Operating Area

IR HiRel radiation hardened MOSFETs have been characterized in heavy ion environment for Single Event Effects (SEE). Single Event Effects characterization is illustrated in Fig. 1 and Table 7.

Table 7 Typical Single Event Effects Safe Operating Area

lan	LET	Energy	Range	V _{DS} (V)				
lon	(MeV·cm²/mg)	(MeV)	(µm)	$V_{GS} = 0V$	$V_{GS} = -5V$	V _{GS} = -10V	V _{GS} = -15V	V _{GS} = -20V
Br	37.9	255	33.4	30	30	30	25	20
	59.4	290	28.8	25	25	20	15	10
Au	80.3	313	26.5	22.5	22.5	15	10	_




Figure 1 Typical Single Event Effect, Safe Operating Area



Electrical Characteristics Curves (Pre-irradiation)

3 Electrical Characteristics Curves (Pre-irradiation)




Figure 2 Typical Output Characteristics

Figure 3 Typical Output Characteristics




Figure 4 Typical Transfer Characteristics

Figure 5 Normalized On-Resistance Vs.
Temperature



Electrical Characteristics Curves (Pre-irradiation)




Figure 6 Typical Capacitance Vs.

Drain-to-Source Voltage

Figure 7 Typical Gate-to-Source Voltage Vs.
Typical Gate Charge




Figure 8 Typical Source-Drain Current Vs.
Diode Forward Voltage

Figure 9 Maximum Safe Operating Area



Electrical Characteristics Curves (Pre-irradiation)




Figure 10 Maximum Drain Current Vs. Case Temperature

Figure 11 Maximum Avalanche Energy Vs.
Junction Temperature




Figure 12 Maximum Effective Transient Thermal Impedance, Junction-to-Case



Test Circuits (Pre-irradiation)

4 Test Circuits (Pre-irradiation)




Figure 13 Gate Charge Test Circuit

Figure 14 Gate Charge Waveform




Figure 15 Unclamped Inductive Test Circuit

Figure 16 Unclamped Inductive Waveform




Figure 17 Switching Time Test Circuit


Figure 18 Switching Time Waveforms



Package Outline

5 Package Outline

Note: For the most updated package outline, please see the website: TO-254AA



BERYLLIA WARNING PER MIL-PRF-19500

Package containing beryllia shall not be ground, sandblasted, machined, or have other operations performed on them which will produce beryllia or beryllium dust. Furthermore, beryllium oxide packages shall not be placed in acids that will produce fumes containing beryllium.

IRHM57Z60

Radiation Hardened Power MOSFET Thru-Hole (TO-254AA)



Revision history

Revision history

Document version	Date of release	Description of changes
	11/18/1999	Datasheet (PD-93787)
Rev A	04/10/2000	Updated drawing
Rev B	08/06/2002	Updated IDSS max for 1000KRad(si)
Rev C	06/29/2016	Updated based on ECN-1120_04401
Rev D	05/27/2022	Updated based on ECN-1120_09018

Trademarks

All referenced product or service names and trademarks are the property of their respective owners.

Edition 2022-05-27

Published by

International Rectifier HiRel Products, Inc.

An Infineon Technologies company El Segundo, California 90245 USA

© 2022 Infineon Technologies AG. All Rights Reserved.

Do you have a question about this document?

Email: erratum@infineon.com

Document reference

IMPORTANT NOTICE

The information given in this document shall in no event be regarded as a guarantee of conditions or characteristics ("Beschaffenheitsgarantie").

With respect to any examples, hints or any typical values stated herein and/or any information regarding the application of the product, Infineon Technologies hereby disclaims any and all warranties and liabilities of any kind, including without limitation warranties of non-infringement of intellectual property rights of any third party.

In addition, any information given in this document is subject to customer's compliance with its obligations stated in this document and any applicable legal requirements, norms and standards concerning customer's products and any use of the product of Infineon Technologies in customer's applications.

The data contained in this document is exclusively intended for technically trained staff. It is the responsibility of customer's technical departments to evaluate the suitability of the product for the intended application and the completeness of the product information given in this document with respect to such application.

For further information on the product, technology, delivery terms and conditions and prices please contact your nearest Infineon Technologies office (www.infineon.com).

WARNINGS

Due to technical requirements components may contain dangerous substances. For information on the types in question please contact your nearest International Rectifier HiRel Products, Inc., an Infineon Technologies company, office.

International Rectifier HiRel Components may only be used in life-support devices or systems with the expressed written approval of International Rectifier HiRel Products, Inc., an Infineon Technologies company, if failure of such components can reasonably be expected to cause the failure of that life-support device or system, or to affect the safety and effectiveness of that device or system.

Infineon Technologies' products may not be used in any applications where a failure of the product or any consequences of the use thereof can reasonably be expected to result in personal injury.

Life support devices or systems are intended to be implanted in the human body, or to support and/or maintain and sustain and/or protect human life. If they fail, it is reasonable to assume that the health of the user or other persons may be endangered.